MS17/12PIU-6 V10

Product summary:

DiSEqC multiswitch with integrated power supply, 0 to 15 dB attenuators, Quad LNB compatible, switchable active/passive terr. input



Brief description:

17in/12out standalone multiswitch for distribution of 16 SAT IF signals including terrestrial for up to 12 users

Technical data:

Parameter	Condition	Value
Frequency range	LNB inputs	950-2300 MHz
	Terr. input	5-862 MHz (passive), 40-862 MHz (active)
	Outputs	5-2300 MHz (passive), 40-2300 MHz (active)
Control		DiSEqC 1.0 (2.0) commands
Insertion loss	Sat.	0 dB avg
	Terr. passive	19 dB avg
	Terr. active	5 dB avg
Sat. inputs isolation	Between V/H polarisations	20 dB min
	Between low/high bands	20 dB min
	Between sat. systems	25 dB min
Maximum input level*	Sat.	90 dBµV avg**
	Terr.	100 dBµV avg (passive), 90 dBµV avg (active)
Maximum output level*	Sat.	90 dBµV avg
	Terr.	81 dBµV avg (passive), 85 dBµV avg (active)
Power consumption	From each receiver	75 mA (18 V)
	From internal power supply	4.5 W (passive), 6.5 W (active) + LNB
Terr. preamplifier supply		150 mA max (12 V DC)
Dimensions (w,d,h)		47.0 x 15.2 x 8.7 cm, (power cord length 130 cm)
Temperature range		-30 ~ +70 °C
Weight		1.900 kg

*Terr.: EN 50083-3/60dB IMA3 [dBµV]; SAT: EN 50083-3/35dB IMA3 [dBµV]

Production status:

In production (status is valid to date: 2014/11/09)

Postal address: EMP-Centauri s.r.o. 5. kvetna 690 339 01 Klatovy Czech Republic
Management: Tel.: +420 376 323 812 Tel.: +420 376 314 852 E-mail: info@emp-centauri.cz
Sales department: Tel.: +420 376 323 813   +420 778 066 744 Fax: +420 376 323 809 E-mail: sales@emp-centauri.cz
Purchase department: E-mail: purchase@emp-centauri.cz
Technical support: Tel.: +420 376 323 853 (during workhours)Hotline: +420 603 497 419 (available anytime)E-mail: support@emp-centauri.cz